

Fire Alarm Mains Isolator Keyswitch

Part No. **BF326 Range**



Overview

- Allows the mains to a fire alarm control panel to be switched on or off as per the requirements of BS5839-1.
- Available in red or white with or without an LED Indicator (surface or flush).
- Double pole.
- Fitted with 5A Fuse.
- Supplied with a special key that is only available to the responsible person.
- Able to be wired with 1 x 2.5mm² cable or 2 x 1.5mm² cable to ensure only independent sole main supplies are used to the fire panel as per BS5839-1 requirements.
- Can be labelled for use with an Evacuation Alert or Emergency Voice Communication System (EVCS) using a BF326/LABEL.
- In stock and available to purchase today



More Information

Technical Specifications

Approvals/certifications	Designed to comply with the requirements of BS 5839-1
Type	Double pole, lockable, 230V
Mains rated current	5A.
Supply/operating voltage	230 VDC.
Quiescent current	2mA if LED, 0mA if no LED,
Indicators	Green if LED fitted.
IP Rating	IP30.



Operating conditions/temperature -5°C to +40°C. Max. relative humidity 95% non-condensing.

Construction & finish Red or White PVC.

Product dimensions (mm) Switch Plate 86 x 86 mm x 25 or (25.7mm deep with LED), with supplied back box fitted 54mm deep.

Weight TBC.

Notes Key type: Red C-TEC S-Key.



T 01942 322744 E sales@c-tec.co.uk

F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom