

Emergency Lighting Test Switches

Emergency lighting test switches provide a cost effective solution for the testing of emergency luminaires.

It is a legal requirement that all emergency luminaires are tested on a regular basis to ensure they provide adequate escape illumination.

Load Capacity Key

Suitable for the control of:



Lighting

ELT10



This automatic key operated emergency lighting test switch is permanently wired to the emergency luminaire supply.

The key switch is used to interrupt the supply for pre-programmed periods. At the end of the time period, the supply to the luminaires is automatically reinstated. The result is that there is no risk of depleting the batteries in the emergency fitting by leaving them connected for prolonged periods. The key switch ensures secure access.

Test Periods: 10 minutes, 1 hour and 3 hours.

Order Code	Description				
ELT10	Automatic emergency test switch				
Load Rating at 230VAC					
R	I	F	CF	LED	
N/A	N/A	6A	3A	3A	
R = Resistive I = Incandescent F = Fluorescent CF = Compact Fluorescent					

Please note: A single ELT10 is suitable for switching one circuit, for multiple circuit applications see ELT-REL.